### HOUSING

Made from aluminum and coated with a smooth matte finish.

SOLAR CHARGER

When solar charging the indicator dots will light up for 4 sec. and show how much the battery is charged.





### HANDEL

Portable lamp that can be positioned standing or hung using the integrated handle.

### **ELECTRONIC UNIT**

Casing of recycled plastic. Waterproof IP65. Solar and wireless charger built in.

# 3 LIGHT INTENSITY LEVELS

Press switch pin to turn ON-OFF / Adjust the brightness to suit your needs and mood: 1st press: on 100% light 2nd press: change to 50% light 3rd press: change to 10% light

Long press will switch off the light in any position.

Battery indicator dots illuminate 4 sec. wh switching on.



## **BATTERY LIFE**

Without charging: 8h-100h. Depending on light intensity level.

## **GLASS DOME**







## HOUSING

Made from aluminum and coated with a smooth matte finish.



### **CHARGING PAD**

Wireless charging with the option to power up smartphones and other devices. While charging, the indicator dots will illuminate to display the battery level for 4 sec. The charging pad must be used in a dry place.

Charging time: Approx. 4 hours from 0 % - 100%



OUTDOOR/





(((4))



























## TECHNICAL INFORMATION

Charger Battery Light type Kelvin

Wireless charger input voltage

Wireless charging 3,6V Lithium, 2600 mAh LED 2500K 1W/95 lm 9V DC

Power supply Input

Output

Frequency band H-Field

100-240V AC 50-60 Hz 0,5A USB-C 5V DC 3A 9 DC 2,22A 12V DC 1.67A 110,6 KHz to 146,8 KHz -20,29 dBpA/m @ 10 m

Wireless charger for the lamp enclosed

The luminaires shall be supplied by an independent separated extra-low voltage (SELV) power source, which should be certified with standard EN 61347-2-13 (Class II, IP20 or higher, fail-safe, or short circuit proof, with suitable output ratings, and maximum output voltage shall not exceed 60 VDC).

## MAINTENANCE

Use a soft cloth with lukewarm water. Avoid any kind of chemical detergents.

## REPAIR

The product can be disassembled, allowing for the replacement of technical components. For spare part information, please contact your HOUE point of sale.

The light source contained in this luminaire shall only be replaced by the manufacturer, service agent or similar qualified person.